

WHAT'S NEW

SAN Access Module

MODELS

StorageWorks™ Smart Array 5300 Controller by Compaq

Smart Array 5304/128 Controller

158939-B21

158939-291 (Japan)

Smart Array 5302/64 Controller

124992-B21

124992-291 (Japan)

Smart Array 5302/32 Controller

166207-B21

166207-291 (Japan)

Smart Array 5302/FC Controller

216688-B21

216688-291 (Japan)

Feature List:

- Advanced RAID level: Advanced Data Guarding*
- High Performance Architecture
- Innovative modular design
 - Upgradable cache for higher performance
 - Upgradable from 2 to 4 SCSI channels
 - SAN Access Module
- High Capacity
 - 2 channel models support up to 28 drives
 - 4 channel models support up to 56 drives
- Multiple battery-backed cache options
 - 32 MB, 64 MB, 128 MB

OVERVIEW

The Smart Array 5300 series of high-performance Ultra3 array controllers provides reliable data protection for Compaq *ProLiant™* servers and offers new levels of flexibility thanks to an innovative modular design and new **Advanced Data Guarding** (RAID ADG) technology. The Smart Array 5300 controller raises the standard to higher performance levels with several enhancements including a new memory architecture and new RAID engine.

Designed and tested with industry-standard ProLiant Servers for greater reliability, this controller is ideal for the distributed workgroup server or centralized departmental server, and like other Smart Array controllers, the SA-5300 offers complete data compatibility with previous generations' Smart Array controllers for easy data migration and upgradability.

KEY FEATURES

- **Advanced Data Guarding** (RAID ADG) offers breakthrough level of fault protection of RAID volumes up to 2TB and a total of 56 disk drive in a RAID volume. RAID ADG provides fault protection greater than RAID 1 or RAID 5 and only consume the capacity of 2 disk drives for distributed parity data. RAID ADG protects against any 2 disk drive failures. This higher level of protection is ideal to protect large logical volumes and with high capacity disk drives where a failed drive rebuild time may be significant.

Note: RAID ADG is a standard feature of SA-5304/128 and available as an option to other models. RAID ADG requires a minimum of 64MB battery backed cache.

COMPAQ

KEY FEATURES *(continued)*

- **Modular**, easy-to-upgrade design lets you optimize performance and increase capacity as needed, from two to four channels and with 32-, 64- or 128-MB battery-backed cache.
- **High-performance**, Fifth generation architecture offers the new hardware RAID engine, and a new performance memory architecture for increased performance over previous controllers.
- **Recovery ROM** protects against a ROM failure or corruption.
- **Ultra3 SCSI** technology delivers high performance and data bandwidth up to 160 MB/s bandwidth per channel.
- **Up to 4 channels** provides the highest storage capacity per PCI slot in the industry.
- **Mix-and-match** LVD SCSI compatibility protects your investments and lets you deploy drives as needed.
- **Battery-backed Cache** protects cached data in the event of a power outage, server failure or controller failure, and redundant, replaceable batteries take that protection even further.
- **64-bit, 66 MHz PCI** interface boosts bandwidth up to a 533 MB/s total transfer rate.
- **64-bit memory addressing** supports servers with greater than 4 GB of memory.
- **Online Management Features:** Online Capacity Expansion, Online RAID Level Migration, Online Stripe Size Migration, Online Spares (Global), User Selectable Read/Write cache, User Selectable Expand and Rebuild Priority
- **SAN Access**, the industry's first integrated SCSI controller and Fibre Channel SAN adapter offers centralized, consolidated backup solutions and incremental SAN based primary storage for groups of 5-10 servers driving Direct Attach Storage (SCSI) with Smart Array 5302 Controllers.

THE SMART ARRAY ADVANTAGE

Compaq's innovative design and integration work of the Smart Array family of products creates customer value that is unmatched in the industry. Use of Smart Array products across multiple applications results in a much lower Total Cost of Ownership (TCO) than any other server storage RAID products. The Compaq Smart Array family brings an unparalleled return on investment through:

Data Compatibility among all models of Smart Array controllers allows simple and easy upgrades any time needs for higher performance, capacity, and availability increase. Even successive generations of Smart Array controllers understand the data format of other Smart Array Controllers.

Consistent Configuration and Management Tools. All Smart Array products utilize a standard set of management and utility software. These tools minimize Total Cost of Ownership (TCO) by reducing training requirements and technical expertise necessary to install and maintain the Compaq server storage.

Universal Hard Drive form factor is for use across multiple Compaq servers, disk enclosures and storage systems. With compatibility across many enterprise platforms, you are free to deploy and re-deploy these drives to quickly deliver increased storage capacity, migrate data between systems, and easily manage spare drives.

Pre-Failure Warranty means Compaq Insight Manager not only reports when a drive is going to fail but allows replacement of failing drives prior to actual failure. For complete details, consult the Compaq Support Center or refer to your Compaq Server documentation.

PRODUCT HIGHLIGHTS

Data Compatibility

Data compatibility among all models of Smart Array Controllers means customers can instantly upgrade their Smart Array products to get to higher performance, capacity and availability. Unlike competitive products, successive generations of Smart Array products understand the data format of other Smart Array controllers, providing investment protection for your Compaq storage solution.

Performance

Compaq's new high-performance architecture sets new boundaries of industry performance expectations!

- Wide Ultra3 SCSI (160 MB/s bandwidth) per channel
- High-performance 64-bit architecture, featuring a super-scalar RISC processor
- New RAID XOR engine
- New performance memory architecture providing tri-directional data flow for improved performance
- 64-bit, 66-MHz PCI bus (533-MB/s bandwidth)

PRODUCT HIGHLIGHTS *(continued)*

Capacity

Given the need for scalable capacity growth of server storage, the SA-5300 offers up to four SCSI channels for over two terabytes of storage from a single PCI slot:

- Modular design offering 2 & 4 channel models plus, an Ultra3 channel expansion card offering 2 additional external SCSI channels for SA-5300 models with 2 channels
- 4 channel models support up to 56 hard drives (4 TB = 72.8 GB x 56 hard drives)
- 2 channel models support up to 28 hard drives (2 TB = 72.8 GB x 28 hard drives)

Availability

Provides increased server uptime by providing advanced storage functionality:

- Online RAID Level Migration (between any RAID level)
- Online Capacity Expansion
- Logical Drive Capacity Extension
- Global Online Spare
- Pre-Failure Warranty

Fault Prevention

The following features offer detection of possible failures before they occur, allowing preventive action to be taken:

- S.M.A.R.T.: Self Monitoring Analysis and Reporting Technology first developed at Compaq detects possible hard disk failure before it occurs, allowing replacement of the component before failure occurs.
- Drive Parameter Tracking monitors drive operational parameters, predicting failure and notifying the administrator.
- Dynamic Sector Repairing continually performs background surface scans on the hard disk drives during inactive periods and automatically re-maps bad sectors, ensuring data integrity.
- Smart Array Cache Tracking monitors integrity of controller cache, allowing pre-failure preventative maintenance.
- Environment Tracking for External Storage System monitors

Fault Tolerance

Keeps data available and server running while a failed drive is being replaced; several fault tolerance configurations are supported including:

- **Advanced Data Guarding** (RAID ADG): This is the highest level of fault tolerance. It allocates two sets of parity data across drives and allows simultaneous write operations. This level of fault tolerance can withstand two simultaneous drive failures without downtime or data loss. It is available standard with SA-5304/128 and as an option to other models. Requires a minimum of 64MB battery backed cache.
- **Distributed Data Guarding** (RAID 5): This allocates parity data across multiple drives and allows simultaneous write operations. It is recommended for up to 14 hard drives.
- **Drive Mirroring** (RAID 1, 1+0): This allocates half of the drive array to data and the other half to mirrored data, providing two copies of every file. It is a high-performance RAID.

Fault Recovery

Minimizes downtime, reconstructs data, and facilitates a quick recovery from drive failure

- **Recovery ROM:** provides a unique redundancy feature that protects from a ROM failure. A new version of firmware can be flashed to the ROM while the controller maintains the last known working version of firmware. If the firmware becomes corrupt, the controller will revert back to the previous version of firmware and continue operating. This reduces the risk of flashing firmware to the controller.
- **On-Line Spares:** Up to four spare drives can be installed prior to drive failure. If a failure occurs, recovery begins with an On-Line Spare and data is reconstructed automatically.
- **ECC-Protected Cache Memory:** Removable, battery-backed cache memory protects data, up to four days, in the event of power failure, server hardware failure or controller failure. In addition, Compaq provides an exclusive design that includes **redundant and replaceable batteries** for greater cache protection.
 - 128-MB and 64-MB Cache modules also feature **Chip Recovery**, protecting the cache memory from a single chip failure and multi-bit errors from any single memory chip.

PRODUCT HIGHLIGHTS *(continued)*

Ease of Use

Consistency and Upgradability make the Smart Array family unique in the industry:

- GUI based configuration, management and diagnostic software tools
- Common data formatting between generations of products
- Data migration between servers and external storage enclosures

SAN Access (Optional)

The SAN Access Module for the Smart Array 5302 Controller offers the industry's first true integrated bridge from Direct Attach Storage (SCSI) to the Fibre Channel Storage Area Network (SAN). Fibre Channel SAN offers robust data handling for superior reliability and manageability. Smart Array SAN Access Technology grants users of SCSI based storage the opportunity to implement a basic SAN for the consolidation of backup operations with Compaq Enterprise Backup Solutions (ARCPaq or BackPaq). SAN Access Technology also offers access to primary storage (RAID Array 4100) on the SAN.

Key Features:

- 1 Gbit bandwidth offering 100 MB/s of peak data transfer
- Reduction in PCI slot utilization: both Direct Attach Storage and SAN access on a single PCI slot
- Centralized backup of Direct Attach Storage through the Enterprise Backup Solution (EBS) using either ARCPaq or BackPaq software
- Access to incremental SAN based primary storage (RAID Array 4100) when using the FC-AL Switch 8
- Qualified on ProLiant servers running Microsoft Windows NT/2000 and Novell NetWare

Servers Compatibility

For up to date compatibility, please see the following URL for complete Smart Array 5300 compatibility and support information.

<http://www.compaq.com/products/StorageWorks/array-and-scsi-controllers/SA5300index.html>

Operating Systems Compatibility

Microsoft Windows NT 4.0, 2000 **

Novell NetWare 4.2, 5.x **

SCO UnixWare 7.1.x

SCO OpenServer 5.0.4, 5.0.5

Linux

IBM OS/2 Warp Server 4 *

IBM OS/2 Warp Server for e-Business

Sun Solaris™ * Intel Platform Edition 7

* Not supported on day of announcement.

**SAN Access module compatible with Operating System.

SOFTWARE SUITE

All Smart Array products share a common set of configuration, management and diagnostic tools, including Array Configuration Utility XE (ACU-XE), Array Configuration Utility (ACU), Array Diagnostic Utility (ADU), and Insight Manager. This software consistency of tools reduces the cost of training for each successive generation of product and takes much of the guesswork out of troubleshooting field problems. These tools lower the total cost of ownership by reducing training and technical expertise necessary to install and maintain the Compaq server storage.

Compaq Insight Manager

- Powerful server and server options/storage manager tool
- Monitors over 1200 server parameters

SOFTWARE SUITE *(continued)*

Configuration/Diagnostic Utilities

- Compaq Array Configuration Utility (ACU)
 - Powerful configuration utility for all Smart Array controllers
 - Provides a graphical view of Compaq drive array configurations
 - Easy to use Wizards for configuration
- Compaq Array Configuration Utility XE (ACU-XE)
 - Easy to use Wizards for configuration Powerful Web based configuration utility for all Smart Array controllers
 - Provides a graphical view of Compaq drive array configurations
 - Allows for management of multiple arrays over a secure internet connection from anywhere in the world
 - Easy to use Wizards for configuration
 - Runs online on NT v4.0, Windows 2000 and NetWare
- Compaq Array Diagnostic Utility (ADU)
 - Powerful diagnostic utility for all Smart Array controllers
- Options ROM Configuration Capability
 - Rapid configuration upon initial install of the OS

SPECIFICATIONS

Electrical Interface	LVD (Low Voltage Differential) and SE (Single Ended)	
Protocol Support	Wide Ultra3 SCSI (160 MB/s per channel)	
SCSI Ports	4 channel model: 4 external/2 Internal shared 2 channel model: 2 external/2 internal shared	
Drives Supported	4 channel model: up to 56 drives 2 channel model: up to 28 drives	
Maximum Capacity	4 channel model: 4 TB (56 drives x 72.8 GB) 2 channel model: 2 TB (28 drives x 72.8 GB)	
PCI	PCI 2.2 Compliant	
PCI Bus Speed	64-bit, 66-MHz PCI (533 MB/s maximum bandwidth)	
Logical Drives	Up to 32 logical drives	
RAID Support	RAID ADG (Advanced Data Guarding)* included with model SA-5304/128 RAID 5 (Distributed Data Guarding) RAID 1+0 (Striping & Mirroring) RAID 0 (Striping)	
Cache Memory	Up to 128 MB Read/Write (32-, 64-, 128-MB modules) ECC protection, battery-backed, and removable SA-5302/FC comes standard with 32MB cache memory	
Cache Batteries	Up to 4 days of redundant battery life, removable for easy replacement	
Upgradeable Firmware	2-MB flashable ROM	
Disk Drive and Enclosure Protocol Support	Ultra3, Ultra2 and Wide-Ultra (SCSI-3)	
Memory Addressing	64-bit, supporting servers memory greater than 4 GB	
Dimensions (HxWxD)	18.375 x 8.25 x 4 in/46.67 x 20.95 x 10.16 cm	
Weight	Smart Array 5304/128	3.26 lbs/1.48 kg
	Smart Array 5302/64	3.12 lbs/1.42 kg
	Smart Array 5302/32	3.12 lbs/1.42 kg
	Smart Array 5302/FC	3.62 lbs/1.65 kg
	SAN Access Module	2.00 lbs/0.91 kg

SPECIFICATIONS *(continued)*

SAN Access Module Specifications

Fibre Channel Protocol Support **	1 Gbit Fibre Channel
Fibre Channel Ports **	1
EBS Qualification **	ARCPaq and BackPaq Note: Only with single (non-cascaded) 7 or 12 Port Fibre Channel Hub and FC-AL Switch 8
SAN Primary Storage Qualification **	RAID Array 4100 Note: Access to volume (LUN) created by separate Compaq Fibre Channel Host Bus Adapter and assigned under Selective Storage Presentation and only with a single (non-cascaded) FC-AL Switch 8 ** Fibre Channel support is a standard feature of the SA-5302/FC and available as an option to other models. Fibre Channel support requires the SAN Access Module.

SERVICE & SUPPORT, CAREPAQ AND WARRANTY INFORMATION

Available Software Product Services

- Standalone telephone support
- Rights to new license version
- Media and documentation updates

Available Hardware Product Services

- Installation services
- On-site maintenance (includes warranty support)
- Response time upgrades during the warranty period
- Post-warranty coverage
- RAID setup and performance consulting via statement of work

For additional hardware installation and maintenance information, please refer to the URLs listed below:

<http://www.compaq.com/services/carepag/us/install/>

<http://www.compaq.com/services/carepag/us/hardware/>

Warranty Upgrade Options

- Response - Upgrade on-site response from next business day to same day 4 hours
- Coverage - Extend hours of coverage from 9 hours x 5 days to 24 hours x 7 days
- Duration - Select duration of coverage for a period of 1, 3, or 5 years

CarePaq Information

- CarePaq is defined as an upgrade to the product warranty attribute, available for a specific duration and hours of coverage.
- CarePaq is not available for less than the product's warranty duration.
- CarePaq is available for sale anytime during the warranty period for most products, but the commencement date will be the same as the Warranty Start Date (delivery date to end user customer). Proof of purchase may be required.
- CarePaq services are prepaid.

For additional CarePaq (hardware & software) information, as well as orderable part numbers, please refer to the URL listed below:

<http://www.compaq.com/services/carepag/index.html>

OPTIONS

Controller Upgrade Options	Ultra3 Channel Expansion Module for Smart Array 5300 Controller Note: This is a 2 channel Expansion Module	153507-B21
	128MB Cache Module for Smart Array 5302 Controller Note: This Cache Module is Battery Backed	153506-B21
	Advanced Data Guarding Module for Smart Array 5302 Controller	199371-B21
	SAN Access Module for Smart Array 5302 Controller	216687-B21
	SAN Access Module for Smart Array 5302 Controller (Japan)	216687-291
Software	<i>StorageWorks</i> Virtual Replicator	
	License & Media (CD-ROM)	388931-B21
	License Only	388932-B21
Disk Drive Enclosures	<i>StorageWorks</i> Enclosure 4314T	190210-001
	<i>StorageWorks</i> Enclosure 4314T (Int'l)	190210-B31
	<i>StorageWorks</i> Enclosure 4314T (Japan)	190210-291
	<i>StorageWorks</i> Enclosure 4314R	190209-001
	<i>StorageWorks</i> Enclosure 4314R (Int'l)	190209-B31
	<i>StorageWorks</i> Enclosure 4314R (Japan)	190209-291
	<i>StorageWorks</i> Enclosure 4354R	190211-001
	<i>StorageWorks</i> Enclosure 4354R (Int'l)	190211-B31
	<i>StorageWorks</i> Enclosure 4354R (Japan)	190211-291
Hard Drives	<i>Wide Ultra3 SCSI Universal Drives – Hot Plug</i>	
	36.4-GB Wide Ultra3 SCSI 15,000 rpm Drive (1")	232916-B22
	18.2-GB Wide Ultra3 SCSI 15,000 rpm Drive (1")	188122-B22
	9.1-GB Wide Ultra3 SCSI 15,000 rpm Drive (1")	188120-B22
	72.8-GB Wide Ultra3 SCSI 10,000 rpm Drive (1")	232432-B22
	36.4-GB Wide Ultra3 SCSI 10,000 rpm Drive (1")	176496-B22
	18.2-GB Wide Ultra3 SCSI 10,000 rpm Drive (1")	142673-B22
	9.1-GB Wide Ultra3 SCSI 10,000 rpm Drive (1")	142671-B22
	36-GB Wide Ultra3 SCSI 10,000 rpm Drives (1"), 10 pack	232617-B21
	18-GB Wide Ultra3 SCSI 10,000 rpm Drives (1"), 10 pack	202352-B21
	Note: This is a list of supported hard disk drives (note that some drives may be discontinued).	
	Note: For complete compatibility information, refer to the Compaq SCSI Hard Drive Compatibility table located at http://www.compaq.com/products/StorageWorks/hdd/hotplug.html and http://www.compaq.com/products/StorageWorks/hdd/nonplug.html .	
	Universal Hot Plug Tape Drives	AIT 50GB, Hot Plug
AIT 35GB, LVD Hot Plug		216886-B21
20/40-GB DAT, Hot Plug		215488-B21

FAMILY INFORMATION

This is a brief overview and comparison of the Smart Array family of PCI RAID controllers.

	Smart Array 5300	Smart Array 4200	Smart Array 3200	Smart Array 431	Smart Array 4250ES
Introduction Date	July 2000	July 1999	September 1998	January 2000	August 1999
SCSI Protocols Supported	Ultra3, Ultra2, Wide-Ultra	Ultra2, Wide-Ultra	Ultra2, Wide-Ultra	Ultra3, Ultra2, Wide-Ultra	Ultra2, Wide-Ultra
Maximum Channel Transfer Rate (MB/s)	640 total 160 per channel	320 total 80 per channel	160 total 80 per channel	160 total 160 per channel	120 total 40 per channel
Channels	2, 4	4	2	1	3
SCSI Ports (external/internal)	2 channel model: 2/2 4 channel model: 4/2	4/2	2/2	1/1	0/3
Maximum Drives	56 ♦	56 ♦	28 ♦	14 ♦	21 ♦♦
Cache	128-, 64- or 32-MB read-write	64-MB read-write	64-MB read-write	16-MB cache engine	64-MB read-write
Battery-backed, Removable Cache	Yes, Redundant, Replaceable Batteries	Yes	Yes	No	Yes
Recovery ROM	Yes	No	No	No	No
RAID Support	0,1,1+0,5, Advanced Data Guarding *	0,1,1+0,5	0,1,1+0,4,5	0,1,1+0,5	0,1,1+0,5
Configuration Tool(s)	ACU-XE ACU ORCA	ACU-XE ACU	ACU-XE ACU	ACU-XE ACU ORCA	ACU-XE ACU
Management and Diagnostic Tools	CIM ADU	CIM ADU	CIM ADU	CIM ADU	CIM ADU
Maximum Volumes	32	32	32	32	32
Drive Roaming	Yes	Yes	Yes	Yes	Yes
Online Expansion	Yes	Yes	Yes	Yes	Yes
Online & Offline Configuration	Yes	Yes	Yes	Yes	Yes
Logical Drive Extension	Yes	Yes	Yes	Yes	Yes
Stripe Set Migration	Yes	Yes	Yes	Yes	Yes
RAID Level Migration	Yes	Yes	Yes	Yes	Yes
Redundant Controllers	No	No	No	No	Yes
Online Spare Support	Yes	Yes	Yes	Yes	Yes
Capacity Extension	Yes	Yes	Yes	Yes	Yes
SAN Access Module	Yes	No	No	No	No
PCI Bus	64-bit, 66-MHz	64-bit, 33-MHz	32-bit, 33-MHz	64-bit, 66-MHz	64-bit, 33-MHz

- ♦ Based on use of *StorageWorks* Enclosure 4200/4300 family (14 drives enclosure)
- ♦♦ Based upon use in ProLiant 8000/ProLiant ML750 which support 21 disk drives
- * RAID ADG is a standard feature of SA-5304/128 and available as an option to other models. RAID ADG requires a minimum of 64MB battery backed cache.

CONFIGURATION INFORMATION

Building a Storage Sub-System with the Smart Array 5300 Controller

STEP 1 – SMART ARRAY 5300 – CHOOSE A MODEL

Select one:

<u>Model Number</u>	<u>Part Number</u>	<u>Model Description</u>
SA-5302/32	166207-B21	Smart Array 5302/32 Controller
	166207-291 (Japan)	Ultra3 2 channel PCI Array Controller board, 32-MB cache module, Setup and configuration software, Documentation
SA-5302/64	124992-B21	Smart Array 5302/64 Controller
	124992-291 (Japan)	Ultra3 2 channel PCI Array Controller board, 64-MB cache module, Setup and configuration software, Documentation
SA-5304/128	158939-B21	Smart Array 5304/128 Controller
	158939-291 (Japan)	Ultra3 2 channel PCI Array Controller board, Ultra3 2 channel Expansion Module, 128-MB Cache module, Advanced Data Guarding, Setup and configuration software, Documentation
SA-5302/FC	216688-B21	Smart Array 5302/FC Controller
	216688-291 (Japan)	Ultra3 2 channel PCI Array Controller board, SAN Access Module, 32-MB Cache module, Setup and configuration software, Documentation

STEP 2 – OPTIONS FOR THE CONTROLLER

Select each required option with quantities specified.

<u>Part Number</u>	<u>Quantity</u>	<u>Description with Parts Shipped</u>
153507-B21		Ultra3 Channel Expansion Module for Smart Array 5300 Controller
153506-B21		128MB Cache Module for Smart Array 5302 Controller
199371-B21		Advanced Data Guarding Module for Smart Array 5302 Controller
388931-B21		<i>StorageWorks</i> Virtual Replicator (CD Media & License)
216687-B21		SAN Access Module for Smart Array 5302 Controller
216687-291		SAN Access Module for Smart Array 5302 Controller (Japan)

CONFIGURATION INFORMATION *(continued)*

STEP 3 – ADDITIONAL OPTIONS

Select each required option with quantities specified.

<u>Part number</u>	<u>Quantity</u>	<u>Description with Parts Shipped:</u>
190210-001		StorageWorks Enclosure 4314T
190210-B31		StorageWorks Enclosure 4314T (Int'l)
190210-291		StorageWorks Enclosure 4314T (Japan)
190209-001		StorageWorks Enclosure 4314R
190209-B31		StorageWorks Enclosure 4314R (Int'l)
190209-291		StorageWorks Enclosure 4314R (Japan)
190211-001		StorageWorks Enclosure 4354R
190211-B31		StorageWorks Enclosure 4354R (Int'l)
190211-291		StorageWorks Enclosure 4354R (Japan)
232432-B22		72.8-GB Pluggable Wide Ultra3 Universal 10,000 rpm Drive (1")
232916-B22		36.4-GB Pluggable Wide Ultra3 Universal 15,000 rpm Drive (1")
176496-B22		36.4-GB Pluggable Wide Ultra3 Universal 10,000 rpm Drive (1")
188122-B22		18.2-GB Pluggable Wide Ultra3 Universal 15,000 rpm Drive (1")
142673-B22		18.2-GB Pluggable Wide Ultra3 Universal 10,000 rpm Drive (1")
188120-B22		9.1-GB Pluggable Wide Ultra3 Universal 15,000 rpm Drive (1")
142671-B22		9.1-GB Pluggable Wide Ultra3 Universal 10,000 rpm Drive (1")
215487-B21		AIT 50GB, Hot Plug Tape Drive
216886-B21		AIT 35GB, LVD Hot Plug Tape Drive
215488-B21		20/40-GB DAT, Hot Plug Tape Drive
234453-001		7 Port Fibre Channel Hub **
234453-B31		7 Port Fibre Channel Hub (Int'l) **
234453-291		7 Port Fibre Channel Hub (Japan) **
295573-001		12 Port Fibre Channel Hub **
295573-B31		12 Port Fibre Channel Hub (Int'l) **
295573-291		12 Port Fibre Channel Hub (Japan) **
177862-B21		SW FC-AL Switch 8 **
177862-291		SW FC-AL Switch 8 (Japan) **
177863-B21		SW FC-AL Switch expansion port **
146013-001		RA4100 (rack mountable) **
146013-B31		RA4100 (rack mountable) (Int'l) **
146013-291		RA4100 (rack mountable) (Japan) **
152975-001		FC Tape Controller- II (NA) **
152975-B31		FC Tape Controller- II (Int'l) **
152975-291		FC Tape Controller- II (Japan) **
160999-B21		EBS BackPaq (Hub 7, MDR, Backup Exec) **
189960-B21		EBS ARCPaq (Hub 7, MDR, ARCserve) **
380561-B21		FC Optical GBIC **

** Fibre Channel support is a standard feature of the SA-5302/FC and available as an option to other models. Fibre Channel support requires the SAN Access Module.

NOTE: This is a list of additional supported options – some may be discontinued.